

Amendments to the Claims:

This listing of claims will replace all prior versions, and listings, of claims in the application:

Listing of Claims:

1. (Currently amended) An output buffer circuit comprising:
a plurality of unit circuits in each of which a pull-up transistor controlled by a first input signal is connected between a high-potential power supply and common node, and a first pull-down transistor controlled by a second input signal and a second pull-down transistor controlled by a third input signal are connected in series between said common node and a low-potential power supply;
an output terminal connected to a common connecting point of said common nodes of said plurality of unit circuits; ~~and~~
first resistors formed respectively between said common nodes of said plurality of unit circuits and said common connecting point; and
second resistors formed respectively between said high-potential power supply and pull-up transistor and between said pull-down transistor and low-potential power supply in each of said plurality of unit circuits.
2. (Currently amended) An output buffer circuit comprising:
a plurality of unit circuits in each of which a plurality of pull-up transistors controlled by an input signal are connected in series between a high-potential power supply and common nodes, and a plurality of pull-down transistors controlled by an input signal are connected in series between said common nodes and a low-potential power supply;
an output terminal connected to a common connecting point of said common nodes of said plurality of unit circuits; and

first resistors formed respectively between said common nodes of said plurality of unit circuits and said common connecting point; and

third resistors formed respectively between said pull-up transistors and common nodes and between said common nodes and pull-down transistors in each of said plurality of unit circuits.

3. (Canceled)

4. (Currently amended) The output buffer circuit according to claim [[3]] 1, wherein said plurality of second resistors formed respectively between said high-potential power supply and pull-up transistor and between said pull-down transistor and low-potential power supply have the same resistance.

5. (Canceled)

6. (Currently amended) The output buffer circuit according to claim [[5]] 2, wherein said plurality of third resistors formed respectively between said pull-up transistors and common nodes and between said common nodes and pull-down transistors have the same resistance.

7. (Previously presented) The output buffer circuit according to claim 2, wherein said plurality of first resistors formed between said common nodes and output terminal have the same resistance.

8. (Previously presented) The output buffer circuit according to claim 2, wherein each of said pull-up and pull-down transistors is a MIS transistor.

9. (Previously presented) The output buffer circuit according to claim 2, wherein said plurality of pull-up transistors have the same gate length and the same gate width, and said plurality of pull-down transistors have the same gate length and the same gate width.

10. (Previously presented) The output buffer circuit according to claim 2, wherein said resistor is selected from the group consisting of a metal film, composite metal film, metal cermet film, polysilicon film, diffusion layer, and transistor.

11-14. (Canceled)

15. (Currently amended) A semiconductor memory comprising:
a plurality of memory cells;
a plurality of terminals including an output terminal; and
an output buffer circuit positioned adjacent to said memory cell, said output buffer circuit comprising a plurality of unit circuits in each of which a pull-up transistor controlled by a first input signal is connected between a high-potential power supply and common node and a pull-down transistor controlled by a second input signal is connected between said common node and a low-potential power supply, and comprising first resistors connected respectively between said common nodes of said plurality of unit circuits and a common connecting point of said common nodes,

wherein said first resistors are formed between said output buffer circuit and output terminal, and

wherein, if the number of said first resistors is an even number, said first resistors are symmetrically arranged with respect to a central line of said output buffer circuit and output terminal, and have the same value, the same size, and the same shape.

16-17. (Canceled)

18. (Currently amended) A semiconductor memory comprising:
a plurality of memory cells;
a plurality of terminals including an output terminal; and
an output buffer circuit positioned adjacent to said memory cell, said output buffer circuit comprising a plurality of unit circuits in each of which a pull-up transistor controlled by a first input signal is connected between a high-potential power supply and common node and a pull-down transistor controlled by a second input signal is connected between said common node and a low-potential power supply, and comprising first resistors connected respectively between said common nodes of said plurality of unit circuits and a common connecting point of said common nodes.

~~The semiconductor memory according to claim 15,~~

wherein said first resistors are formed between said output buffer circuit and output terminal and said first resistors are formed on at least not less than one of three sides of said output terminal, which do not oppose said output buffer circuit.

19. (Previously presented) The semiconductor memory according to claim 18, wherein if the number of first resistors is two, said first resistors are symmetrically

Appl. No. 10/721,310

Attorney Docket No. 81788.0261

Amdt. Dated April 26, 2007

Customer No.: 26021

Reply to Final Office Action of February 2, 2007

arranged in portions of said output terminal, which do not oppose said output buffer circuit, and have the same value, the same size, and the same shape.